

FBXSB01 : Wireless remote control alarm system

Technical specification

FORBIX SEMICON



Model: FBXSB01

Wireless siren alarm receiver

Features:

- 108db loud siren
- 1 indicator RED light in the front
- 1 indicator BLUE SYNC light to check signal reception

Technical details:

Operating frequency: 380 – 480 MHz

System works on signal hop mechanism. Reception happens at more than 12-15 predefined frequencies

Modulation type: GFSK

Radio IC: CC1100 (Chipcon/TI) and equivalents in sub-GHz freq.

Receiver sensitivity: – 112 dbm

Operating voltage:

110-220VAC/50-60Hz to 12VDC converter adapter supplied.

Unit can also be plugged to any 12V external battery. Active working hours depends on the battery power

Signal transmissions:

Make sure to press transmitter panic button for at least 2-3 seconds for reliable transmission. This increases the range of communication

Application and features:

- Alerts building security or maintenance staff in case of emergency from anywhere inside the building
 - Mounted on the top of door of hospital wards / office / patient rooms / guest house rooms / hotel suites etc.
- Loud 108db siren sound when panic button is pressed

Range of communication:

- 20 – 30 meters indoors
- 100 – 120 meters outdoors (line of sight)

Precautions and mounting locations:

- Remotes mounted on the top of door / wall
- Easy mounting of remote jacket with 2 screws
- For indoor outdoor purpose use only
- Keep away from metallic enclosures
- Do not connect the battery in opposite direction
- Receiver unit can mount on the wall

wireless remote siren alarm system unit

Size: 150 x 90 x 55 mm

Weight: 450 gms

FORBIX SEMICON INDIA PVT. LTD.

Bangalore, India

Website: <https://www.forbixindia.com>

+91 9742370190 / +91 9742159846

FORBIX Osühing,

Tallinn, Estonia

Website: <https://www.forbix.eu>

+372 880 1510

Email: sales@forbixindia.com