



Model: FBX622

Handheld wireless remote controller (250-800m) in open line of sight

Features:

- 2 buttons (ON / OFF)
- GREEN button – ON signal
- RED button – OFF signal
- 1 RED light indicator for calling button press indication
- Metal antenna for improved range

Technical details:

- Transmitter PA +15dbm
- Operating frequency: 315– 480 MHz
- System operates works on signal hop mechanism. Signal transmission happens at more than 12-15 predefined frequencies
- Modulation type: GFSK
- Radio IC: CC1100 (Chipcon/TI) sub-GHz frequency
- Data packet error correction mechanism: FEC

Battery and operating voltage:

12 Volt (DC battery)

Battery model: 23A

Battery life: 2-3 years

Battery type: Alkaline (dry)

Battery replaceable: Yes

Battery rechargeable: No

Battery mounting: Bottom

Battery life: 3-4years, depending on the usage

[Make sure to keep the remote in OFF mode, by sliding the OFF switch on the right side. This saves battery and improves life]

RF antenna:

PCB trace antenna / wire coil antenna / metal antenna (depends on environment necessity)

Application and features:

- Panic alarms and siren ON/OFF
- Motor pump ON/OFF
- Gate opening and closing from a distant location
- Nurse call system for hospitals: remote with patients
- Steam bath sauna rooms / spas / restaurants etc.
- OPD token system for dispensaries: remote with doctors
- Office peon calling system: remote with clerk / manager
- Guest house attendant call unit: remote with customers in room

Precautions and mounting locations:

- Mounted on the top of door / wall / bed
- Easy mounting with 4 screws to secure it tightly
- IP65 enclosure unit, robust and weatherproof
- Keep away from metallic enclosures
- Do not expose battery to water and moisture

Handheld calling unit:

Enclosure type: plastic grey

Remote controller size: 135 x 45 x 28 mm

Antenna length: 185 mm

Remote controller weight: 130 gms

Range of communication:

• 50-80 meters indoors (depending on environmental condition)

• 500-800 meters outdoors (in clear and open line of sight) with no obstruction

Pressing the button for at least 2-3 seconds improves the range of communication

FORBIX SEMICON INDIA PVT. LTD.

Bangalore, india

Website: <https://www.forbixindia.com>

+91 9742370190 / +91 9742159846

FORBIX Osäuhing,

Tallinn, Estonia

Website: <https://www.forbix.eu>

+372 880 1510

Email: sales@forbixindia.com